

ECONOMY TROFFER RETROFIT KIT



JAYKAL

PROJECT NAME:

JAYKAL LED SOLUTIONS, INC.

www.jaykal.net

PROJECT NOTES:

26832 Lewes Georgetown Hwy,
Building 2, Unit E
Harbeson, DE 19951
(P) 302-295-0015
(F) 302-295-0016

DESCRIPTION:

The simple design of the Retrofit Kit provides maximum light distribution and is ideal for commercial and industrial applications. Engineered for a quick and easy installation into existing 1X4, 2x2 and 2x4 fixtures, this one piece retrofit kit and is quick to install and provides for years of worry free energy efficient lighting.

FEATURES & BENEFITS:

- ◆ **5 Minute Install**
- ◆ Wattage Options: 18, 24, or 36 Watt
- ◆ CCT Options: 3000K, 4000K, 5000K
- ◆ 125+lm/W
- ◆ Options: 0-10V Dimming
- ◆ One Piece Retrofit Kit
- ◆ 5 Year Warranty
- ◆ Near Zero Maintenance



5 YEAR STANDARD WARRANTY—EXTENDED WARRANTIES AVAILABLE

(P) 302-295-0015 | (E) sales@jaykal.net | (W) www.jaykal.net

Specifications are typical values and may change without notification

efficiency. illuminated.


ECONOMY TROFFER RETROFIT KIT





JAYKAL

SPECIFICATIONS TABLE

Model.	18W	24W	36W
Input Voltage	100-277VAC	100-277VAC	100-277VAC
Wattage	18W	24W	36W
Efficacy	125 lm/W	125 lm/W	125 lm/W
Lumens	2,250 lm	3,750 lm	4,500 lm
Power Factor	>0.9	>0.9	>0.9
THD	<15%	<15%	<15%
CRI	>80	>80	>80
CCT	3000k/4000k/5000k	3000k/4000k/5000k	3000k/4000k/5000k
Operational Temperature	-30°C — 50°C	-30°C — 50°C	-30°C — 50°C
Housing Material	Aluminum	Aluminum	Aluminum



2 x 2 and 2 x 4 Troffer Retrofit



1 x 4 Troffer Retrofit

ORDERING GUIDE

MODEL NUMBER	-	WATTAGE	-	SIZE	-	CCT	-	OPTIONS
JLS68102-ETS		18 = 18W 24 = 24W 36 = 36W		1 = 1X4 2 = 2X2 4 = 2X4 12 = 1X2		30K = 3000K 40K = 4000K 50K = 5000K		OC = Occupancy Sensor EM = Emergency Backup 10V = 0-10V Dimming 50 = 50-50 Dimming

(P) 302-295-0015 | (E) sales@jaykal.net | (W) www.jaykal.net

Specifications are typical values and may change without notification

efficiency. illuminated.